REPLACEMENT PARTS LIST

CAUTION: BEFORE REPLACING ANY OF THESE COMPONENTS,
READ CAREFULLY THE **SAFETY PRECAUTIONS** IN THIS MANUAL.
* NOTE : **S** SAFETY Mark
AL ALTERNATIVE PARTS

MODEL: StudioWorks 45i DATE: 1997. 4. 1.

*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		MAIN BOARD			
		CAPACITORs			
		C401	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C402	0CE1056K618	CAPACITOR, ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C403	0CC2200K405	CAPACITOR, 22P 50V J SL, TP	
		C404	0CC2200K405	CAPACITOR, 22P 50V J SL, TP	
		C421	181-288G	CAPACITOR, POLYESTER, MKT 100V 334JTR PHS26334	
		C424	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C451	0CK2210K515	CAPACITOR, 220P 50V K B TS	
		C461	0CK2210K515	CAPACITOR, 220P 50V K B TS	
		C462	0CK2210K515	CAPACITOR, 220P 50V K B TS	
		C463	0CK2210K515	CAPACITOR, 220P 50V K B TS	
		C601	0CE1086F630	CAPACITOR, AL.ELECTROLYTIC, 1000M SMS 16V M FM5	
		C603	0CC6800K405	CAPACITOR, 68P 50V J SL, TP	
		C604	0CE4766L618	CAPACITOR, AL.ELECTROLYTIC, 47 UF SMS,SG 63V M FL TP	
		C606	181-288D	CAPACITOR, POLYESTER, MKT 100V 473JTR PHS26473	
		C621	181-310D	CAPACITOR, AL.ELECTROLYTIC, CE SM-BP(D) 50V 1UF TP 5	
		C622	181-305A	CAPACITOR, POLYPROPYLENE, MPP 250V 104J S=10.0	
		C625	0CK1020K515	CAPACITOR, CERAMIC (HIGH DIELECTRIC) 1000PF 50V K	
		C701	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C702	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C703	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C704	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C705	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C706	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C707	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C708	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C709	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C710	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C711	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C712	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C713	0CE2256K618	CAPACITOR, 2.2U SMS 50V M FM5 TP5	
		C721	181-288R	CAPACITOR, POLYESTER, MKT 100V 123JTR PHS86123	
		C722	181-288N	CAPACITOR, POLYESTER, MKT 100V 103JTR PHS86103	
		C723	0CQ3321N419	CAPACITOR, 3300P 100V J POLY NI TP	
		C724	181-288T	CAPACITOR, POLYESTER, MKT 100V 223KTR PHS85223	
		C725	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C726	181-288C	CAPACITOR, POLYESTER, MKT 100V 224JTR PHS 26224	
		C731	0CK5610K515	CAPACITOR, 560P 50V K B TS	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		C732	181-288C	CAPACITOR, POLYESTER, MKT 100V 224JTR PHS 26224	
⚠		C733	0CK2220K515	CAPACITOR, 2200P 50V K B TS	
⚠		C734	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C735	0CE4766H618	CAPACITOR, 47M SMS 25V M FL TP(5)	
		C736	0CE2256K618	CAPACITOR, 2.2U SMS 50V M FM5 TP5	
		C739	0CK4710W515	CAPACITOR, 470PF 500V K B TR	
		C740	0CK4710W515	CAPACITOR, 470PF 500V K B TR	
		C741	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C742	181-314K	CAPACITOR, AL.ELECTROLYTIC, SMSHR 200V 47UF 16X25	
		C743	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C751	0CC4710K405	CAPACITOR, CERAMIC TEMP COMPENSATE470P 50V J SL TP	
		C752	0CE1076F618	CAPACITOR, 100UF SMS 16V M TP(5)	
		C753	0CQ1021N419	CAPACITOR, 1000P 100V J POLY NI TP	
		C755	181-305W	CAPACITOR, POLYPROPYLENE, MPP 250V 604J S=15.0	
⚠		C756	181-309Q	CAPACITOR, POLYPROPYLENE, BUP 1.6KV 562J S=20.0	
		C757	181-306J	CAPACITOR, POLYPROPYLENE, PU 800V 472J S=10.0	
		C758	181-302Q	CAPACITOR, POLYPROPYLENE, PL 200V 153J S=10.0 143F	
		C759	0CK10201515	CAPACITOR, 1000P 1KV K B TS	
		C761	0CE4766F618	CAPACITOR, 47U SMS 16V M FM5 TP5	
		C762	181-288D	CAPACITOR, POLYESTER, MKT 100V 473JTR PHS26473	
		C763	0CQZTBU002F	CAPACITOR, POLYESTER, MPE 100V 335PF(31*19*20)	
		C764	181-305J	CAPACITOR, POLYPROPYLENE, MPP 250V 474J S=15.0 128B	
		C765	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C766	0CK2220K515	CAPACITOR, 2200P 50V K B TS	
		C771	181-305C	CAPACITOR, POLYPROPYLENE, MPP 250V 154J S=10.0	
		C772	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C773	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C774	181-305G	CAPACITOR, POLYPROPYLENE, MPP 250V 334J S=10.0	
		C775	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C776	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C777	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
⚠		C781	0CE2266H618	CAPACITOR, 22M SMS 25V M FM5 TP(5)	
		C782	0CE1056K618	CAPACITOR, ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C783	0CK1030W510	CAPACITOR, 0.01U 500V K B S	
		C784	0CE2266K618	CAPACITOR, 22M SMS 50V M FM5 TP(5)	
		C785	0CE4756P618	CAPACITOR, 4.7U SMS 160V M FM5 TP5	
		C786	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C787	0CE1056K618	CAPACITOR, ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C788	0CE1056K618	CAPACITOR, ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C789	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C791	0CK1030W510	CAPACITOR, 0.01U 500V K B S	
		C792	0CE1056R618	CAPACITOR, 1.0U SMS 250V M FM5 TP5	
⚠		C793	0CE2266K618	CAPACITOR, 22M SMS 50V M FM5 TP(5)	
⚠		C901	0CBZTBU002A	CAPACITOR, BULK, PCX2 335 224K	
⚠	or	C901	181-500B	CAPACITOR, MKT, 335, 10224M, PHILIPS	
⚠	or	C901	181-192E	CAPACITOR, KNB1531, 0.22UF 250V, ISKRA	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
⚠		C902	0CBZTBU002C	CAPACITOR, POLYPROPYLENE, BULK PCX2 335 104K	
⚠	or	C902	181-500A	CAPACITOR, MKT, 335, 10104M, PHILIPS	
⚠	or	C902	181-192A	CAPACITOR, KNB1531, 0.1UF 250V, ISKRA	
⚠		C903	181-311C	CAPACITOR, CERAMIC (HIGH DIELECTRIC) DE7150-477F472M	
⚠		C904	181-311C	CAPACITOR, CERAMIC (HIGH DIELECTRIC) DE7150-477F472M	
⚠		C908	181-296F	CAPACITOR, AL.ELECTROLYTIC, 330UF 400V (30*40)	
		C911	0CE3376H630	CAPACITOR, ELECTROLYTIC, 330M SMS 25V M FM5	
		C912	0CE335BN638	CAPACITOR, AL.ELECTROLYTIC, 3.3000UF KME 100V M FM5	
		C913	0CE1076H618	CAPACITOR, 100M SMS 25V M FM5 TP(5)	
		C914	0CQ1521N419	CAPACITOR, POLYESTER, 1500PF 100V J PE NI TP	
		C915	0CE105BN638	CAPACITOR, 1.0U KME 100V M FM5 TP5	
		C916	181-308N	CAPACITOR, POLYPROPYLENE, PL 630V 103J S=10.0 061K	
		C917	0CK56101515	CAPACITOR, 560P 1KV K B TS	
		C918	0CK5610K515	CAPACITOR, 560P 50V K B TS	
⚠		C921	181-311C	CAPACITOR, CERAMIC (HIGH DIELECTRIC) DE7150-477F472M	
		C932	0CE107CP630	CAPACITOR, AL.ELECTROLYTIC, 100UF SHL 160V M FM5	
		C934	0CE227CN630	CAPACITOR, AL.ELECTROLYTIC, 220U SHL 100V M FM5	
		C935	0CE108CH630	CAPACITOR, AL.ELECTROLYTIC, 1000UF SHL 25V M FM5	
		C936	0CE1086F630	CAPACITOR, AL.ELECTROLYTIC, 1000M SMS 16V M FM5	
		C937	0CE4766L618	CAPACITOR, AL.ELECTROLYTIC, 47 UF SMS,SG 63V M FL	
		C943	0CK1030W510	CAPACITOR, 0.01U 500V K B S	
		C944	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C945	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C946	0CE477CF618	CAPACITOR, 470UF SHL 16V M FL TP5	
		C947	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C948	0CE1086F630	CAPACITOR, AL.ELECTROLYTIC, 1000M SMS 16V M FM5	
		C951	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C952	0CE1056K618	CAPACITOR, ELECTROLYTIC, 1.0U SMS 50V M FM5 TP5	
		C953	0CE2266P630	CAPACITOR, AL.ELECTROLYTIC, 22U SMS 160V M FM5	
	DIODEs				
		D411	0DL150320AA	LED, L-1503EB/2GD	
		D412	0DL150320AA	LED, L-1503EB/2GD	
		D413	0DL150320AA	LED, L-1503EB/2GD	
		D414	0DL150320AA	LED, L-1503EB/2GD	
		D415	0DL150320AA	LED, L-1503EB/2GD	
		D416	0DL150320AA	LED, L-1503EB/2GD	
		D421	0DZ510009AB	DIODE, ZENER, MTZ5.1B, TP (52MM), ROHM	
		D422	0DZ510009AB	DIODE, ZENER, MTZ5.1B, TP (52MM), ROHM	
		D423	0DZ510009AB	DIODE, ZENER, MTZ5.1B, TP (52MM), ROHM	
		D461	0DZ510009AB	DIODE, ZENER, MTZ5.1B, TP (52MM), ROHM	
		D462	0DZ510009AB	DIODE, ZENER, MTZ5.1B, TP (52MM), ROHM	
		D621	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D701	0DD300009AC	DIODE, RECTIFIER, RU3AMV(1) TP, SANKEN	
		D713	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D731	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		D732	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D733	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D734	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D735	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D736	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D737	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
⚠		D738	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D739	0DZ470005AA	DIODE, ZENER, MTZ 4.7B, TP, ROHM	
		D741	0DD300000AB	DIODE, RECTIFIER, FMP-3FU, SANKEN	
		D744	0DD547000AB	DIODE, RECTIFIER, 5TUZ47C (LB101A), TOSHIBA	
		D745	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D746	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D751	0DZ820009AA	DIODE, ZENER, MTZ8.2B, TP (52MM), ROHM	
		D761	0DZ150009BD	DIODE, ZENER, MTZ15B, TP (52MM), ROHM	
		D771	0DZ150009BD	DIODE, ZENER, MTZ15B, TP (52MM), ROHM	
		D781	0DZ150009BD	DIODE, ZENER, MTZ15B, TP (52MM), ROHM	
		D783	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D791	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D793	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D794	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D795	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D796	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D797	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D798	0DZ110009AA	DIODE, ZENER, MTZ 11B, TP (52MM), ROHM	
⚠		D901	0DD260000BD	DIODE, BRIDGE, BRIDGE D2SBA60 ,SHINDENKEN	
⚠		D902	0DD100009DA	DIODE, RECTIFIER, RGP10J, TP (52MM), GI	
		D904	0DD220009AA	DIODE, RECTIFIER, RG2A2 TP SANKEN	
		D905	0DD400209DB	DIODE, SWITCHING, IN4002,(52MM) TP, ROHM	
		D906	0DZ820009AA	DIODE, ZENER, MTZ8.2B, TP (52MM), ROHM	
		D907	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D908	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D909	0DD100009DD	DIODE, RECTIFIER, RGP10D, TP (52MM), GI	
		D911	0DD100009AH	DIODE, RECTIFIER, ES1FV(1) TP, SANKEN	
		D931	0DD200009AH	DIODE, RECTIFIER, RU2AMV(1) TP, SANKEN	
		D932	0DD410000AF	DIODE, RECTIFIER, RL4A, LF-L1, SANKEN	
		D933	0DD540200AA	DIODE, RECTIFIER, UF5402 (19C2-409),GI	
		D936	0DD540200AA	DIODE, RECTIFIER, UF5402 (19C2-409),GI	
		D937	0DD100009DE	DIODE, RECTIFIER, RGP10G, TP (52MM), GI	
		D941	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D942	0DL571300AA	LED (LIGHT EMITTED DIODE), SPR571MVW3, ROHM	
		D951	0DZ510009AB	DIODE, ZENER, MTZ5.1B, TP (52MM), ROHM	
	ICs				
		IC401	0IMO730021A	IC, MOTOROLA, LGM730-021/L5 42 BK MICOM_MASK 14”	
		IC402	0IKE704200B	IC, KEC, KIA7042P(AT) TO-92 4.2V RESET	
		IC403	0IAL240410A	IC, ATMEL, AT24C04-10PC 8D EEPROM (4K,IIC)	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
	or	IC403	0IXI240400B	IC, XICOR, X24C04P, 8D, EEPROM (4K,IIC)	
	or	IC403	0IAL240410A	IC, NATIONAL SEMICONDUCTOR, NM24C04N8D, EEPROM	
		IC601	0IPH486630A	IC, PHILIPS, TDA4866/V3D	
⚠		IC701	0IPH485800A	IC, PHILIPS, TDA4858	
⚠		IC901	0ISK571700A	IC, SANKEN, STR-5717	
		IC931	0IKE780500K	IC, KEC, KIA7805PI 3P (TO-220IS) 5V, 1A	
	or	IC931	0IGS780500A	IC, LG, GL7805 (TO-220IS) 5V, 1A	
	COILs & CORES				
		L483	125-022J	CORE (CIRC), BEAD FERRITE, KQ-1(TAPING)	
		L484	125-022J	CORE (CIRC), BEAD FERRITE, KQ-1(TAPING)	
		L701	6140TBZ003A	COIL,CHOKE D/D CHOKE,EI2519,160UH	
		L702	125-155J	CORE (CIRC), FERRITE, BEAD (BFS2550A0FG), SAMHWA	
		L731	125-022J	CORE (CIRC), BEAD FERRITE, KQ-1(TAPING)	
		L732	150-985G	COIL, CHOKE 8*11, 10MH, R/CENTER	
⚠		L733	150-L05F	COIL, LINEARITY 14*15, 7.8UH, CS485	
		L734	125-022J	CORE (CIRC), BEAD FERRITE, KQ-1(TAPING)	
		L735	125-054C	CORE (CIRC), FERRITE, 0P6,35*10*2.6	
		L751	150-518S	COIL, CHOKE 14X20 180UH	
⚠		L901	6200TLE001B	FILTER, LINE L/FILTER (EE2229), 15MIN, C485	
⚠		L902	150-509D	FILTER (CIRC), LINE 150-509D LG L/FILTER,1.8MH, 14*7*7.5	
		L903	125-155M	CORE (CIRC), FERRITE, BEAD (BFD3550R2FG), SAMHWA	
⚠		L921	6210TCB001A	CORE (CIRC), BEAD BOAM 6H0LE 3T	
		L922	6210TCS001A	CORE (CIRC), BEAD BFR505025D6NI, SAMWHA 5*5*3 4T	
		L923	125-155G	CORE (CIRC), FERRITE, BEAD (BFS3550R2FG), SAMHWA	
		L932	0LA2200K139	INDUCTOR, AXIAL LEAD 220 UH 10% A 4.0 X 10.5 TA52	
	TRANSISTORs				
		Q411	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q412	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q413	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q414	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q417	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q451	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q452	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q453	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q621	0TR320609AB	TRANSISTOR, KTC3206-Y,TP (KTC2229),KEC	
		Q701	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q704	0TF640000BB	FET, IRFS640, SAMSUNG	
		Q720	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q721	0TR200009AB	TRANSISTOR, KTC200-Y, TP, KEC	
		Q722	0TR949009BA	TRANSISTOR, 2SA949-Y TP, TOSHIBA	
		Q724	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q729	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q730	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	

MODEL: StudioWorks 45i				DATE: 1997. 4. 1.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		Q731	0TR512900AA	TRANSISTOR, 2SC5129, TOSHIBA	
		Q740	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q741	0TR126609AA	TRANSISTOR, KTA1266-Y (KTA1015) TP, KEC	
		Q742	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q743	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q751	0TR126609AA	TRANSISTOR, KTA1266-Y (KTA1015) TP, KEC	
		Q752	0TR126609AA	TRANSISTOR, KTA1266-Y (KTA1015) TP, KEC	
		Q753	0TR141400AC	TRANSISTOR, KTD141 4(TO22OIS) CUTTING BK, KEC	
		Q754	0TR114009AB	TRANSISTOR, DTC114ES, TP, ROHM	
		Q756	0TR102609AC	TRANSISTOR, KTC1026-Y (KTC2230A), TP	
		Q761	0TF630000BA	FET, IRFS 630, SAMSUNG	
	or	Q761	0TF630000AA	FET, YTAF 630, TOSHIBA	
		Q762	0TR320709AA	TRANSISTOR, KTC3207, TP(KTC2482), KEC	
		Q771	0TF630000BA	FET, IRFS 630, SAMSUNG	
	or	Q771	0TF630000AA	FET, YTAF 630, TOSHIBA	
		Q772	0TR320709AA	TRANSISTOR, KTC3207,TP(KTC2482), KEC	
		Q781	0TF630000BA	FET, IRFS 630, SAMSUNG	
	or	Q781	0TF630000AA	FET, YTAF 630, TOSHIBA	
		Q782	0TR320709AA	TRANSISTOR, KTC3207, TP (KTC2482), KEC	
		Q901	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q902	0TR200009AB	TRANSISTOR, KTC200-Y, TP, KEC	
		Q932	0TR127309AA	TRANSISTOR, KTA1273-Y TP (KTA966A), KEC	
		Q934	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q935	0TR127309AA	TRANSISTOR, KTA1273-Y TP (KTA966A), KEC	
		Q936	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q941	0TR320209AA	TRANSISTOR, KTC3202-TP-Y (KTC1959), KEC	
		Q942	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
		Q943	0TR319809AA	TRANSISTOR, KTC3198-TP-Y (KTC1815), KEC	
	RESISTORs				
		R401	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R402	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R403	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R404	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R405	0RD1802F609	RESISTOR, FIXED CARBON FILM, 18K 1/6W 5 TA52	
		R406	0RD1802F609	RESISTOR, FIXED CARBON FILM, 18K 1/6W 5 TA52	
		R407	0RD1802F609	RESISTOR, FIXED CARBON FILM, 18K 1/6W 5 TA52	
		R408	0RD1802F609	RESISTOR, FIXED CARBON FILM, 18K 1/6W 5 TA52	
		R409	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R410	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R411	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R412	0RD5600F609	RESISTOR, FIXED CARBON FILM, 560 1/6W 5 TA52	
		R413	0RD5600F609	RESISTOR, FIXED CARBON FILM, 560 1/6W 5 TA52	
		R414	0RD5600F609	RESISTOR, FIXED CARBON FILM, 560 1/6W 5 TA52	
		R415	0RD5600F609	RESISTOR, FIXED CARBON FILM, 560 1/6W 5 TA52	

MODEL: StudioWorks 45i				DATE: 1997. 4. 1.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R416	0RD5600F609	RESISTOR, FIXED CARBON FILM, 560 1/6W 5 TA52	
		R417	0RD5600F609	RESISTOR, FIXED CARBON FILM, 560 1/6W 5 TA52	
		R418	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R421	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R422	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R423	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R424	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R425	0RD3302F609	RESISTOR, FIXED CARBON FILM, 33K 1/6W 5% TA52	
		R427	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R428	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R429	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R430	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R431	0RD1202F609	RESISTOR, FIXED CARBON FILM, 12K 1/6W 5 TA52	
		R441	0RD1000F509	RESISTOR, FIXED CARBON FILM, 100 1/6W 2 TA52	
		R442	0RD1000F509	RESISTOR, FIXED CARBON FILM, 100 1/6W 2 TA52	
		R443	0RD1001F509	RESISTOR, FIXED CARBON FILM, 1K 1/6W 2 TA52	
		R444	0RD1001F509	RESISTOR, FIXED CARBON FILM, 1K 1/6W 2 TA52	
		R445	0RD9100F509	RESISTOR, FIXED CARBON FILM, 910 1/6W 2 TA52	
		R446	0RD5600F509	RESISTOR, FIXED CARBON FILM, 560 1/6W 2 TA52	
		R447	0RD1001F509	RESISTOR, FIXED CARBON FILM, 1K 1/6W 2 TA52	
		R448	0RD6800F509	RESISTOR, FIXED CARBON FILM, 680 1/6W 2 TA52	
		R451	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R452	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R453	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R454	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R455	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R456	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R457	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R461	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R462	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R463	0RD3001F609	RESISTOR, FIXED CARBON FILM, 3.0K 1/6W 5 TA52	
		R464	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R465	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R466	0RD5100F609	RESISTOR, FIXED CARBON FILM, 510 1/6W 5 TA52	
		R471	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R472	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R473	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R479	0RD2200F609	RESISTOR, FIXED CARBON FILM, 220 1/6W 5 TA52	
		R601	0RN0101H609	RESISTOR, 1.0 1/2W 5 TA52	
		R602	0RD0102H609	RESISTOR, FIXED CARBON FILM, 10 1/2W 5% TA52	
		R603	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5 TA52	
		R604	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5 TA52	
		R605	0RD1802F609	RESISTOR, FIXED CARBON FILM, 18K 1/6W 5 TA52	
		R606	0RN0101H609	RESISTOR, 1.0 1/2W 5 TA52	
		R607	0RD2001F609	RESISTOR, FIXED CARBON FILM, 2.0K 1/6W 5 TA52	
		R609	0RD1800H609	RESISTOR, FIXED CARBON FILM, 180 1/2W 5 TA52	

MODEL: StudioWorks 45i				DATE: 1997. 4. 1.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R610	0RD0102G609	RESISTOR, FIXED CARBON FILM, 10 1/4W 5 TA52	
		R621	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R622	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R623	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R624	0RD1502G609	RESISTOR, FIXED CARBON FILM, 15K 1/4W 5 TA52	
		R625	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R626	971-0016	WIRE, TIN HDC 0.60H	
		R701	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R702	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R703	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R704	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R705	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R706	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R707	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R708	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R709	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R710	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R711	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R712	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R713	0RD2702F609	RESISTOR, FIXED CARBON FILM, 27K 1/6W 5 TA52	
		R714	0RD2702F609	RESISTOR, FIXED CARBON FILM, 27K 1/6W 5 TA52	
		R715	0RD2702F609	RESISTOR, FIXED CARBON FILM, 27K 1/6W 5 TA52	
		R716	0RD2702F609	RESISTOR, FIXED CARBON FILM, 27K 1/6W 5 TA52	
		R717	0RD1502F609	RESISTOR, FIXED CARBON FILM, 15K 1/6W 5 TA52	
		R718	0RD2002F609	RESISTOR, FIXED CARBON FILM, 20K 1/6W 5 TA52	
		R721	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R722	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R723	0RN1001F409	RESISTOR, FIX METAL FILM, 1K 1/6W 1% TA52	
		R724	0RN1801F409	RESISTOR, FIX METAL FILM, 1.80K 1/6W 1% TA52	
		R725	0RD8201F609	RESISTOR, FIXED CARBON FILM, 8.2K 1/6W 5 TA52	
		R726	0RD2002F609	RESISTOR, FIXED CARBON FILM, 20K 1/6W 5 TA52	
		R727	0RD8202F609	RESISTOR, FIXED CARBON FILM, 82K 1/6W 5 TA52	
		R728	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R730	0RD3301F609	RESISTOR, FIXED CARBON FILM, 3.3K 1/6W 5 TA52	
		R731	0RD1502F609	RESISTOR, FIXED CARBON FILM, 15K 1/6W 5 TA52	
		R732	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R734	0RD2203F609	RESISTOR, FIXED CARBON FILM, 220K 1/6W 5 TA52	
		R735	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R736	0RD1001G609	RESISTOR, FIXED CARBON FILM, 1.0K 1/4W 5 TA52	
		R737	0RD0102F609	RESISTOR, FIXED CARBON FILM, 10 1/6W 5 TA52	
⚠		R738	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R739	180-490B	RESISTOR, VARIABLE, RWN 7W 2.2 OHH J V-TYPE	
		R741	0RD2204F609	RESISTOR, FIXED CARBON FILM, 2.2M 1/6W 5 TA52	
		R742	0RD1802F609	RESISTOR, FIXED CARBON FILM, 18K 1/6W 5 TA52	
		R743	0RD2203F609	RESISTOR, FIXED CARBON FILM, 220K 1/6W 5 TA52	
		R744	0RD4703F609	RESISTOR, FIXED CARBON FILM, 470K 1/6W 5 TA52	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R745	0RD5601F609	RESISTOR, FIXED CARBON FILM, 5.6K 1/6W 5 TA52	
		R746	0RD3003F609	RESISTOR, FIXED CARBON FILM, 300K 1/6W 5 TA52	
		R747	0RD1503H609	RESISTOR, FIXED CARBON FILM, 150K 1/2W 5 TA52	
		R748	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R749	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R750	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R751	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R752	0RD0472F609	RESISTOR, FIXED CARBON FILM, 47 1/6W 5% TA	
		R753	0RD1001Q609	RESISTOR, FIXED CARBON FILM, 1K 1/4W(3 5% TA52	
		R755	0RD0102G609	RESISTOR, FIXED CARBON FILM, 10 1/4W 5 TA52	
		R756	0RS3300J607	RESISTOR, FIX METAL FILM, OXIDE 330 OHM 1 W 5% TA62	
		R758	0RD4700H609	RESISTOR, FIXED CARBON FILM, 470 1/2W 5% TA52	
		R760	0RD3000G609	RESISTOR, FIXED CARBON FILM, 300 1/4W 5 TA52	
		R761	0RD6801F609	RESISTOR, FIXED CARBON FILM, 6.8K 1/6W 5 TA52	
		R762	0RD8200G609	RESISTOR, FIXED CARBON FILM, 820 1/4W 5 TA52	
		R763	0RD3900F609	RESISTOR, FIXED CARBON FILM, 390 1/6W 5 TA52	
		R764	0RD7501F609	RESISTOR, FIXED CARBON FILM, 7.5K 1/6W 5 TA52	
		R765	0RD2200F609	RESISTOR, FIXED CARBON FILM, 220 1/6W 5 TA52	
		R766	0RD1802G609	RESISTOR, FIXED CARBON FILM, 18K 1/4W 5% TA52	
		R768	0RD1801F609	RESISTOR, FIXED CARBON FILM, 1.8K 1/6W 5 TA52	
		R769	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R770	0RD2002F609	RESISTOR, FIXED CARBON FILM, 20K 1/6W 5 TA52	
		R772	0RD1503H609	RESISTOR, FIXED CARBON FILM, 150K 1/2W 5 TA52	
		R773	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R774	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R775	0RD3301F609	RESISTOR, FIXED CARBON FILM, 3.3K 1/6W 5 TA52	
		R776	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R777	0RS0101J607	RESISTOR, FIX METAL FILM, OXIDE 1 OHM 1 W 5% TA62	
		R778	0RS0101J607	RESISTOR, FIX METAL FILM, OXIDE 1 OHM 1 W 5% TA62	
		R779	0RD1001H609	RESISTOR, FIXED CARBON FILM, 1.0K 1/2W 5 TA52	
		R781	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R782	0RD1503H609	RESISTOR, FIXED CARBON FILM, 150K 1/2W 5 TA52	
		R783	0RD2202F609	RESISTOR, FIXED CARBON FILM, 22K 1/6W 5 TA52	
		R784	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R785	0RD3301F609	RESISTOR, FIXED CARBON FILM, 3.3K 1/6W 5 TA52	
		R786	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R787	0RD2200F609	RESISTOR, FIXED CARBON FILM, 220 1/6W 5 TA52	
		R788	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R789	0RD3900H609	RESISTOR, FIXED CARBON FILM, 390 1/2W 5 TA52	
⚠		R790	0RN0470H609	RESISTOR, FIX METAL FILM, 0.47 1/2W 5 TA52	
⚠		R791	0RD2002F509	RESISTOR, FIXED CARBON FILM, 20K 1/6W 2 TA52	
⚠		R792	0RD4702F509	RESISTOR, FIXED CARBON FILM, 47K 1/6W 2% TA52	
⚠		R793	0RD3602F509	RESISTOR, FIXED CARBON FILM, 36K 1/6W 2% TA52	
		R794	0RD1002F509	RESISTOR, FIXED CARBON FILM, 10K 1/6W 2 TA52	
		R795	0RD3003F609	RESISTOR, FIXED CARBON FILM, 300K 1/6W 5 TA52	
		R796	0RD1501F609	RESISTOR, FIXED CARBON FILM, 1.5K 1/6W 5 TA52	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R797	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R798	0RD9102F509	RESISTOR, FIXED CARBON FILM, 91K 1/6W 2% TA52	
		R799	0RD0222H609	RESISTOR, FIXED CARBON FILM, 22 1/2W 5 TA52	
		R811	0RN0470H609	RESISTOR, FIX METAL FILM, 0.47 1/2W 5 TA52	
		R813	0RN0470H609	RESISTOR, FIX METAL FILM, 0.47 1/2W 5 TA52	
		R824	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R825	0RD5602F609	RESISTOR, FIXED CARBON FILM, 56K 1/6W 5 TA52	
		R827	0RD1103F609	RESISTOR, FIXED CARBON FILM, 110K 1/6W 5 TA52	
		R828	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R829	0RD2702F609	RESISTOR, FIXED CARBON FILM, 27K 1/6W 5 TA52	
		R830	0RD3902F609	RESISTOR, FIXED CARBON FILM, 39K 1/6W 5 TA52	
		R832	0RD5101F609	RESISTOR, FIXED CARBON FILM, 5.1K 1/6W 5 TA52	
		R833	0RD1201F609	RESISTOR, FIXED CARBON FILM, 1.2K 1/6W 5 TA52	
		R840	0RD5101F609	RESISTOR, FIXED CARBON FILM, 5.1K 1/6W 5 TA52	
		R841	0RD8202F609	RESISTOR, FIXED CARBON FILM, 82K 1/6W 5 TA52	
		R843	0RD1202G609	RESISTOR, FIXED CARBON FILM, 12K 1/4W 5 TA52	
		R846	0RD1503F609	RESISTOR, FIXED CARBON FILM, 150K 1/6W 5 TA52	
		R847	0RD5601F609	RESISTOR, FIXED CARBON FILM, 5.6K 1/6W 5 TA52	
		R848	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R849	0RD6201F609	RESISTOR, FIXED CARBON FILM, 6.2K 1/6W 5 TA52	
		R851	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R853	0RD2000F609	RESISTOR, FIXED CARBON FILM, 200 1/6W 5 TA52	
		R854	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R855	0RD2201F609	RESISTOR, FIXED CARBON FILM, 2.2K 1/6W 5 TA52	
		R856	0RD1201F609	RESISTOR, FIXED CARBON FILM, 1.2K 1/6W 5 TA52	
		R857	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R859	0RD1502F609	RESISTOR, FIXED CARBON FILM, 15K 1/6W 5 TA52	
		R861	0RN0470H609	RESISTOR, FIX METAL FILM, 0.47 1/2W 5 TA52	
		R871	0RD2204F609	RESISTOR, FIXED CARBON FILM, 2.2M 1/6W 5 TA52	
		R872	0RD1003F609	RESISTOR, FIXED CARBON FILM, 100K 1/6W 5 TA52	
		R873	0RD1003F609	RESISTOR, FIXED CARBON FILM, 100K 1/6W 5 TA52	
⚠		R901	0RD4703H609	RESISTOR, FIXED CARBON FILM, 470K 1/2W 5 TA52	
⚠		R902	0RMZTWD001A	RESISTOR, CEMENT RWR, 5W, 4.7, J, PD-TYPE	
		R903	0RD5603H609	RESISTOR, FIXED CARBON FILM, 560K 1/2W 5 TA52	
		R904	0RD2202H609	RESISTOR, FIXED CARBON FILM, 22K 1/2W 5 TA52	
		R905	0RD2202H609	RESISTOR, FIXED CARBON FILM, 22K 1/2W 5 TA52	
		R906	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R907	0RD6800F509	RESISTOR, FIXED CARBON FILM, 680 1/6W 2 TA52	
		R911	0RS0122J609	RESISTOR, FIX METAL FILM, OXIDE 12 1W 5% TA52	
		R912	0RB0270K607	RESISTOR, FIX WIRE-WOUND PRECISION, 0.27OHM 2 W 5%	
		R915	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R916	0RD0201H609	RESISTOR, FIXED CARBON FILM, 2.0 1/2W 5 TA52	
		R917	0RD0102F609	RESISTOR, FIXED CARBON FILM, 10 1/6W 5 TA52	
		R918	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R921	0RD7502H609	RESISTOR, FIXED CARBON FILM, 75K 1/2W 5 TA52	
		R931	0RD1003H609	RESISTOR, FIXED CARBON FILM, 100K 1/2W 5 TA52	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R933	0RD4700F609	RESISTOR, FIXED CARBON FILM, 470 1/6W 5 TA52	
		R934	0RD8200H609	RESISTOR, FIXED CARBON FILM, 820 1/2W 5 TA52	
		R935	0RD8200H609	RESISTOR, FIXED CARBON FILM, 820 1/2W 5 TA52	
		R936	0RD3902G609	RESISTOR, FIXED CARBON FILM, 39K 1/4W 5 TA52	
		R937	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R938	0RD4700F609	RESISTOR, FIXED CARBON FILM, 470 1/6W 5 TA52	
		R939	0RD1800H609	RESISTOR, FIXED CARBON FILM, 180 1/2W 5 TA52	
		R941	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R945	0RD1803G609	RESISTOR, FIXED CARBON FILM, 180K 1/4W 5 TA52	
		R951	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		R952	0RD8200H609	RESISTOR, FIXED CARBON FILM, 820 1/2W 5 TA52	
		R953	0RD1201H609	RESISTOR, FIXED CARBON FILM, 1.2K 1/2W 5 TA52	
		R954	0RD1001F609	RESISTOR, FIXED CARBON FILM, 1.0K 1/6W 5 TA52	
		R955	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R956	0RD4701F609	RESISTOR, FIXED CARBON FILM, 4.70K 1/6W 5% TA52	
		J13	0RD3901F509	RESISTOR, FIXED CARBON FILM, 3.9K 1/6W 2 TA52	
		VR705	180-038K	VOLUME, EVM-EGS AOOB24	
		VR826	180-038N	VOLUME, EVM-EGS AOOB15	
		VR831	6110T9H001E	VOLUME, 9PHI, B5K, F20, NC, JP, SINGLE	
		VR842	180-038N	VOLUME, EVM-EGS AOOB15	
		VR850	180-038H	VOLUME, EVM-EGS AOOB53	
		VR852	6110T9H001F	VOLUME, 9PHI, B20K, F20, NC, JP, SINGLE	
	OTHERs				
		E2	366-167A	WAFER, BW-501S (17MM)	
		E3	366-167A	WAFER, BW-501S (17MM)	
⚠		F901	131-040C	FUSE, HBC 250V 3.15A UL/S TRIAD	
		P401	366-921E	WAFER, IL-G 6(2.5S)	
		P701	366-139A	PIN, BW-706 (BAEEUN)	
		P702	366-921H	WAFER, IL-G 9(2.5S)	
		P703	366-921H	WAFER, IL-G 9(2.5S)	
		P902	366-921K	WAFER, IL-G 11(2.5S)	
		P903	366-112B	PIN, BW-502L (BAEEUN)	
		P702-P703	6631T25001W	CONNECTOR ASSY 9P,H-H,L100,UL1007#24	
		P902-P302	6631T25001V	CONNECTOR ASSY 11P,H-H,L240,UL1007#24	
		PG1	385-141A	METAL, GROUND	
		PG2	385-141A	METAL, GROUND	
		PG3	385-141A	METAL, GROUND	
⚠		RL901	141-037A	RELAY, OMI-SS-112L	
		SOCKET	6621TAZ002A	SOCKET ASS'Y, HOUSING AC SOCKET	
		SW431	140-058B	SWITCH, TACT EVQ PB2 05K(TP) 160GF	
		SW432	140-058B	SWITCH, TACT EVQ PB2 05K(TP) 160GF	
		SW433	140-058B	SWITCH, TACT EVQ PB2 05K(TP) 160GF	
		SW434	140-058B	SWITCH, TACT EVQ PB2 05K(TP) 160GF	
		SW435	140-058D	SWITCH, TACT SKHV 10911A (7MM)	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		SW731	140-079A	SWITCH, BAND SELECTION (JRS-1301)	
⚠		T701	6174Z-2001J	FBT (FLY BACK TRANSFORMER), FMMPC11	
		T702	151-396H	TRANSFORMER, SIDE PINCUSHION H.D.T (CY581)	
⚠		T901	6170TMZ018A	TRANSFORMER, SMPS EER4042 SI/SC 16-PIN CS485/545	
		TH901	163-053C	THERMISTOR, J502P53D140M220 (JAHWA)	
		X401	156-005B	CRYSTAL, 4.0MHZ(CL.15P)	
	VIDEO BOARD				
	CAPACITORs				
		C301	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C302	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C303	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C304	0CE4766F618	CAPACITOR, 47U SMS 16V M FM5 TP5	
		C305	0CE4766F618	CAPACITOR, 47U SMS 16V M FM5 TP5	
		C306	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C307	0CE1066K618	CAPACITOR, 10M SMS 50V M FM5 TP(5)	
		C311	0CE1066K618	CAPACITOR, 10M SMS 50V M FM5 TP(5)	
		C312	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C313	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C314	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C315	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C316	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C317	0CE4766F618	CAPACITOR, 47U SMS 16V M FM5 TP5	
		C342	0CC6800K415	CAPACITOR, 68P 50V J NP0 TP	
		C343	0CE4756P618	CAPACITOR, 4.7U SMS 160V M FM5 TP5	
		C344	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C345	0CE1056P618	CAPACITOR, 1U SMS 160V M FM5 TP5	
		C352	0CC5600K415	CAPACITOR, 56P 50V J NP0 TP	
		C353	0CE4756P618	CAPACITOR, 4.7U SMS 160V M FM5 TP5	
		C354	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C355	0CE1056P618	CAPACITOR, 1U SMS 160V M FM5 TP5	
		C362	0CC4700K415	CAPACITOR, 47P 50V J NP0 TP	
		C364	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C365	0CE1056P618	CAPACITOR, 1U SMS 160V M FM5 TP5	
		C371	181-288B	CAPACITOR, POLYESTER, MKT 100V 104JTR PHS26104	
		C381	0CN1040K949	CAPACITOR, 0.1UF 50V Z F TA52	
		C382	0CK10201515	CAPACITOR, 1000P 1KV K B TS	
		C383	0CK10201515	CAPACITOR, 1000P 1KV K B TS	
		C384	0CK10201515	CAPACITOR, 1000P 1KV K B TS	
		C391	0CE107CP630	CAPACITOR, AL.ELECTROLYTIC, 100UF SHL 160V M FM5 BULK	
	DIODEs				
		D301	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D302	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D303	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		D304	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D305	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D306	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D331	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D332	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D333	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D341	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D342	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D343	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D344	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D351	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D352	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D353	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D354	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D361	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D362	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D363	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D364	0DD131009AC	DIODE, 1SS131, SWIT TP, ROHM	
		D391	0DZ200009AB	DIODE, ZENER, MTZ20B, TP (52MM), ROHM	
		D392	0DZ240009BB	DIODE, ZENER, MTZ24B, TP (52MM), ROHM	
	ICs				
		IC301	0IMO132810A	IC, MOTOROLA, MC13281BP	
		IC302	0IKE780800B	IC,KEC, KIA78L08BP(TA) TO-92 8V, 150MA	
	COILs & COREs				
		L321	125-155M	CORE (CIRC), FERRITE, BEAD (BFD3550R2FG), SAMHWA	
		L327	125-155G	CORE (CIRC), FERRITE, BEAD (BFS3550R2FG), SAMHWA	
		L328	125-155G	CORE (CIRC), FERRITE, BEAD (BFS3550R2FG), SAMHWA	
		L329	125-155G	CORE (CIRC), FERRITE, BEAD (BFS3550R2FG), SAMHWA	
		L341	0LA0221K119	INDUCTOR, AXIAL LEAD 2.2UH K 2.3*3.4 TP	
		L343	125-155G	CORE (CIRC), FERRITE, BEAD (BFS3550R2FG), SAMHWA	
		L351	0LA0221K119	INDUCTOR, AXIAL LEAD 2.2UH K 2.3*3.4 TP	
		L353	125-155G	CORE (CIRC), FERRITE, BEAD (BFS3550R2FG), SAMHWA	
		L361	0LA0221K119	INDUCTOR, AXIAL LEAD 2.2UH K 2.3*3.4 TP	
		L371	0LA2200K139	INDUCTOR, AXIAL LEAD 220 UH 10% A 4.0 X 10.5 TA52	
		L375	125-155M	CORE (CIRC), FERRITE, BEAD (BFD3550R2FG), SAMHWA	
		L381	125-155F	CORE (CIRC), FERRITE, BEAD (BFD3580R2FG), SAMHWA	
	TRANSISTORs				
		Q331	0TR320609AB	TRANSISTOR, KTC3206-Y, TP (KTC2229), KEC	
		Q332	0TR320609AB	TRANSISTOR, KTC3206-Y, TP (KTC2229), KEC	
		Q333	0TR320609AB	TRANSISTOR, KTC3206-Y, TP (KTC2229), KEC	
		Q341	0TR350200AA	TRANSISTOR, 2SC3502, SANYO	

MODEL: StudioWorks 45i				DATE: 1997. 4. 1.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		Q342	0TR131009BA	TRANSISTOR, BFQ 131 TP, PHILIPS	
		Q343	0TR555109AB	TRANSISTOR, 2N5551 TP	
		Q344	0TR540109AB	TRANSISTOR, 2N5401 TP	
		Q351	0TR350200AA	TRANSISTOR, 2SC3502, SANYO	
		Q352	0TR131009BA	TRANSISTOR, BFQ 131 TP, PHILIPS	
		Q353	0TR555109AB	TRANSISTOR, 2N5551 TP	
		Q354	0TR540109AB	TRANSISTOR, 2N5401 TP	
		Q361	0TR350200AA	TRANSISTOR, 2SC3502, SANYO	
		Q362	0TR131009BA	TRANSISTOR, BFQ 131 TP, PHILIPS	
		Q363	0TR555109AB	TRANSISTOR, 2N5551 TP	
		Q364	0TR540109AB	TRANSISTOR, 2N5401 TP	
		Q391	0TR320609AB	TRANSISTOR, KTC3206-Y, TP (KTC2229), KEC	
	RESISTORs				
		R301	0RD0752F609	RESISTOR, FIXED CARBON FILM, 75 1/6W 5% TA	
		R302	0RD0752F609	RESISTOR, FIXED CARBON FILM, 75 1/6W 5% TA	
		R303	0RD0752F609	RESISTOR, FIXED CARBON FILM, 75 1/6W 5% TA	
		R304	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5 TA52	
		R305	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5 TA52	
		R306	0RD1000F609	RESISTOR, FIXED CARBON FILM, 100 1/6W 5 TA52	
		R311	0RD8201F609	RESISTOR, FIXED CARBON FILM, 8.2K 1/6W 5 TA52	
		R312	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R316	0RD3300F609	RESISTOR, FIXED CARBON FILM, 330 1/6W 5 TA52	
		R317	0RD3300F609	RESISTOR, FIXED CARBON FILM, 330 1/6W 5 TA52	
		R318	0RD3300F609	RESISTOR, FIXED CARBON FILM, 330 1/6W 5 TA52	
		R321	0RD1500F609	RESISTOR, FIXED CARBON FILM, 150 1/6W 5 TA52	
		R322	0RD1500F609	RESISTOR, FIXED CARBON FILM, 150 1/6W 5 TA52	
		R323	0RD1500F609	RESISTOR, FIXED CARBON FILM, 150 1/6W 5 TA52	
		R327	0RD2200F609	RESISTOR, FIXED CARBON FILM, 220 1/6W 5 TA52	
		R328	0RD2200F609	RESISTOR, FIXED CARBON FILM, 220 1/6W 5 TA52	
		R329	0RD2200F609	RESISTOR, FIXED CARBON FILM, 220 1/6W 5 TA52	
		R331	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R332	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R333	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		R334	0RD3902F609	RESISTOR, FIXED CARBON FILM, 39K 1/6W 5 TA52	
		R335	0RD3902F609	RESISTOR, FIXED CARBON FILM, 39K 1/6W 5 TA52	
		R336	0RD3902F609	RESISTOR, FIXED CARBON FILM, 39K 1/6W 5 TA52	
		R337	0RD7502F609	RESISTOR, FIXED CARBON FILM, 75K 1/6W 5 TA52	
		R338	0RD7502F609	RESISTOR, FIXED CARBON FILM, 75K 1/6W 5 TA52	
		R339	0RD7502F609	RESISTOR, FIXED CARBON FILM, 75K 1/6W 5 TA52	
		R341	0RD0562F609	RESISTOR, FIXED CARBON FILM, 56 1/6W 5% TA52	
		R342	0RD0122F609	RESISTOR, FIXED CARBON FILM, 12 1/6W 5 TA52	
		R343	0RMZTSP001A	RESISTOR, CEMENT RSR, 5W, 1.2K, J, P-TYPE	
		R344	0RN0102G609	RESISTOR, FIX METAL FILM, 10 1/4W 5 TA52	
		R345	0RD2701F609	RESISTOR, FIXED CARBON FILM, 2.7K 1/6W 5 TA52	

MODEL: StudioWorks 45i				DATE: 1997. 4. 1.	
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
		R346	0RD1004F609	RESISTOR, FIXED CARBON FILM, 1.0M 1/6W 5 TA52	
		R347	0RN0102G609	RESISTOR, FIX METAL FILM, 10 1/4W 5 TA52	
		R348	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R351	0RD0562F609	RESISTOR, FIXED CARBON FILM, 56 1/6W 5% TA52	
		R352	0RD0122F609	RESISTOR, FIXED CARBON FILM, 12 1/6W 5 TA52	
		R353	0RMZTSP001A	RESISTOR, CEMENT RSR , 5W, 1.2K, J, P-TYPE	
		R354	0RN0102G609	RESISTOR, FIX METAL FILM, 10 1/4W 5 TA52	
		R355	0RD2701F609	RESISTOR, FIXED CARBON FILM, 2.7K 1/6W 5 TA52	
		R356	0RD1004F609	RESISTOR, FIXED CARBON FILM, 1.0M 1/6W 5 TA52	
		R357	0RN0102G609	RESISTOR, FIX METAL FILM, 10 1/4W 5 TA52	
		R358	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R361	0RD0562F609	RESISTOR, FIXED CARBON FILM, 56 1/6W 5% TA52	
		R362	0RD0122F609	RESISTOR, FIXED CARBON FILM, 12 1/6W 5 TA52	
		R363	0RMZTSP001A	RESISTOR, CEMENT RSR, 5W, 1.2K, J, P-TYPE	
		R364	0RN0102G609	RESISTOR, FIX METAL FILM, 10 1/4W 5 TA52	
		R365	0RD2701F609	RESISTOR, FIXED CARBON FILM, 2.7K 1/6W 5 TA52	
		R366	0RD1004F609	RESISTOR, FIXED CARBON FILM, 1.0M 1/6W 5 TA52	
		R367	0RN0102G609	RESISTOR, FIX METAL FILM, 10 1/4W 5 TA52	
		R368	0RD1002F609	RESISTOR, FIXED CARBON FILM, 10K 1/6W 5 TA52	
		R381	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R382	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R383	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R384	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R385	0RD0472H609	RESISTOR, FIXED CARBON FILM, 47 1/2W 5 TA52	
		R391	0RD4702F609	RESISTOR, FIXED CARBON FILM, 47K 1/6W 5 TA52	
		VR313	180-037Q	VOLUME, EVN-DCAA03B24 (MEC), 20KB	
		VR314	180-037Q	VOLUME, EVN-DCAA03B24 (MEC), 20KB	
		VR347	180-038K	VOLUME, EVM-EGS AOOB24	
		VR357	180-038K	VOLUME, EVM-EGS AOOB24	
		VR367	180-038K	VOLUME, EVM-EGS AOOB24	
	OHTERs				
		P301	366-921E	WAFER, IL-G 6(2.5S)	
		P302	366-921K	WAFER, IL-G 11(2.5S)	
		P303	366-167A	WAFER, BW-501S (17MM)	
		P304	366-112B	PIN, BW-502L(BAEEUN)	
		P305	381-199B	SOCKET, CPT PCS626-01(PARK)	
		SG381	165-004A	SPARK GAP, AG20PT 152F-L3N/S-23	
		SG382	165-004A	SPARK GAP, AG20PT 152F-L3N/S-23	
		SG383	165-004A	SPARK GAP, AG20PT 152F-L3N/S-23	
		SG384	165-004A	SPARK GAP, AG20PT 152F-L3N/S-23	
		SG385	165-004A	SPARK GAP, AG20PT 152F-L3N/S-23	

MODEL: StudioWorks 45i					DATE: 1997. 4. 1.
*S	*AL	LOC. NO.	PART NO.	DESCRIPTION / SPECIFICATION	REMARK
	MISCELLANEOUS				
⚠		CRT	2055-10671M	CDT, M34KWW30XX 32N6LD FOR NORTHERN HEMISPHERE	
⚠	or	CRT	2423GA0A36A	CDT, M34KWW30XX 32R6LD FOR EQUATORIAL HEMISPHERE	
		D/COIL	150-A29N	DEGAUSSING COIL	
		G/WIRE	6868T14002A	CDT GROUND, WIRE	
		S/CABLE	6866TA9004G	SIGNAL CABLE, 2990-9C, L1220, IVORY	
	or	S/CABLE	6866TA9004H	SIGNAL CABLE, 2990-9C, L1220, IVORY	
		P/CORD	174-206F	POWER CORD, WALL-OUT, 6FT, IVORY, FOR USA/CAN	